



**UPS
TECNOWARE
1200 Watts
1600 VA Wave
form type
Sinewave
LineInteractive
Phase 1 phase
Desktop/pedestal
FGCERAPL1602SCH**

Modelis: FGCERAPL1602SCH

Gamintojas: TECNOWARE

EAN: 8026475175816

Prekės kodas: 37449

85.99€

UPS ERA PLUS 1600VA, 12V 11Ah battery, It has 1 fixed SCHUKO input cable and 2 SCHUKO outputs protected against blackout, overvoltages and undervoltages. Line Interactive Plus technology. Dimensions 10x14x28 cm, weight 5.5 kg. Equipped with On-Off button with integrated multifunction

Pateikta prekės informacija yra orientacinio pobūdžio. Techninės savybės, nuotraukos, aprašymai ir kaina gali keistis be išankstinio perspėjimo. Gamintojas ir pardavėjas neatsako už galimus duomenų neatitikimus ar tipografines klaidas. Prieš įsigyjant rekomenduojame pasitikrinti aktualią informaciją.

www.shopro.lt | info@shopro.lt | +370 693 39903

LED with audible alarm for signaling the operating status and USB interface for controlling UPS continuity and programming on / off via the free tecnomanager win / mac software. Designed to protect PC Office, DVR for video surveillance, ADSL-Fiber Modem / router, Cash Register. Totally silent.

- Complete protection against blackout and power surges (overvoltages and undervoltages)
- Recommended for Personal Computers, DVR / NVR and video surveillance systems, ADSL / fiber modem, switch / router, cash registers
- Not suitable with power supplies with Active PFC circuit (Server, PC game, video game console, workstation, Mac computer), lamps and electric motors
- AVR Automatic Voltage Regulator electronic circuit
- n 2 Italy / Schuko output sockets and n 1 schuko input cable
- outputs socket protected against blackout
- outputs socket protected against overvoltages
- multifunction LED and on-off button
- USB port for UPS control / monitoring and ignition programming / shutdown via Tecnomanager software
- UPS management software TecnoManager compatible with Windows, Mac OS X, Linux etc

Summary: Tecnoware Era Plus 1600. UPS topology: Line-Interactive, Output power capacity: 1.6 kVA, Output power: 1120 W. AC outlet types: Type F, AC outlets quantity: 2 AC outlet(s), USB port type: USB Type-B. Battery technology: Sealed Lead Acid (VRLA), Typical backup time at full load: 10 min. Form factor: Compact, Product colour: Black, International Protection (IP) code: IP20. Certification: CE | Vendor Homepage: <https://www.tecnoware.com/en-US/Dettaglio/Articolo/56> | Automatic Voltage Regulation (AVR): Yes | Input frequency: 50/60 | Input operation voltage (max): 276 | Input operation voltage (min): 172.5 | Noise level: 40 | Number of input phases: 1 | Number of output phases: 1 | Output frequency: 50/60 | Output operation voltage (max): 230 | Output operation voltage (min): 230 | Output power: 1120 | Output power capacity: 1.6 | Output voltage regulation: 5 | Power factor: 0.7 | Response time: 2 | UPS topology: Line-Interactive | Waveform: Sine | AC outlet types: Type F | AC outlets quantity: 2 | USB 2.0 ports quantity: 1 | USB port: Yes | USB port type: USB Type-B | Battery technology: Sealed Lead Acid (VRLA) | Typical backup time at full load: 10 | Form factor: Compact | International Protection (IP) code: IP20 | LED indicators: Yes | Product colour: Black | Operating altitude: 0 - 300 | Operating relative humidity (H-H): 0 - 95 | Operating temperature (T-T): 0 - 55 | Certification: CE | Depth: 279 | Height: 142 | Weight: 5000 | Width: 101 | Package depth: 340

Pateikta prekės informacija yra orientacinio pobūdžio. Techninės savybės, nuotraukos, aprašymai ir kaina gali keistis be išankstinio perspėjimo. Gamintojas ir pardavėjas neatsako už galimus duomenų neatitikimus ar tipografines klaidas. Prieš įsigyjant rekomenduojame pasitikrinti aktualią informaciją.

www.shoppro.lt | info@shoppro.lt | +370 693 39903

| Package height: 220 | Package width: 180 | Units per Pallet: 0 | Units per Shipping Box: 4 | Unit
Calculated Volume: 0.01312 | Unit Calculated Weight: 4.57

Pateikta prekės informacija yra orientacinio pobūdžio. Techninės savybės, nuotraukos, aprašymai ir kaina gali keistis be išankstinio perspėjimo. Gamintojas ir pardavėjas neatsako už galimus duomenų neatitikimus ar tipografines klaidas. Prieš įsigyjant rekomenduojame pasitikrinti aktualią informaciją.

www.shopro.lt | info@shopro.lt | +370 693 39903